




## Female MP | Female MP



| 零件号               | 产品描述                         | Side A | Side B | ID   | HEX        | L  | MAWP |
|-------------------|------------------------------|--------|--------|------|------------|----|------|
| D9EFA04<br>FA0401 | 1/4 F-MP F-MP 1/4 20k 316D   | 1/4    | 1/4    | 2.8  | 5/8   16   | 36 | 20k  |
| D9EFA04<br>FA0601 | 1/4 F-MP F-MP 3/8 20k 316D   | 1/4    | 3/8    | 2.8  | 3/4   19   | 39 | 20k  |
| D9EFA04<br>FA0901 | 1/4 F-MP F-MP 9/16 20k 316D  | 1/4    | 9/16   | 2.8  | 1   26     | 44 | 20k  |
| D9EFA04<br>FA1201 | 1/4 F-MP F-MP 3/4 20k 316D   | 1/4    | 3/4    | 2.8  | 1+3/8   35 | 50 | 20k  |
| D9EFA04<br>FA1601 | 1/4 F-MP F-MP 1 20k 316D     | 1/4    | 1.00   | 2.8  | 1+3/4   45 | 63 | 20k  |
| D9EFA06<br>FA0601 | 3/8 F-MP F-MP 3/8 20k 316D   | 3/8    | 3/8    | 5.2  | 3/4   19   | 42 | 20k  |
| D9EFA06<br>FA0901 | 3/8 F-MP F-MP 9/16 20k 316D  | 3/8    | 9/16   | 5.2  | 1   26     | 47 | 20k  |
| D9EFA06<br>FA1201 | 3/8 F-MP F-MP 3/4 20k 316D   | 3/8    | 3/4    | 5.2  | 1+3/8   35 | 53 | 20k  |
| D9EFA06<br>FA1601 | 3/8 F-MP F-MP 1 20k 316D     | 3/8    | 1.00   | 5.2  | 1+3/4   45 | 66 | 20k  |
| D9EFA09<br>FA0901 | 9/16 F-MP F-MP 9/16 20k 316D | 9/16   | 9/16   | 9    | 1   26     | 52 | 20k  |
| D9EFA09<br>FA1201 | 9/16 F-MP F-MP 3/4 20k 316D  | 9/16   | 3/4    | 9    | 1+3/8   35 | 58 | 20k  |
| D9EFA09<br>FA1601 | 9/16 F-MP F-MP 1 20k 316D    | 9/16   | 1.00   | 9    | 1+3/4   45 | 71 | 20k  |
| D9EFA12<br>FA1201 | 3/4 F-MP F-MP 3/4 20k 316D   | 3/4    | 3/4    | 13   | 1+3/8   35 | 64 | 20k  |
| D9EFA12<br>FA1601 | 3/4 F-MP F-MP 1 20k 316D     | 3/4    | 1.00   | 13   | 1+3/4   45 | 77 | 20k  |
| D9EFA16<br>FA1601 | 1 F-MP F-MP 1 20k 316D       | 1.00   | 1.00   | 17.5 | 1+3/4   45 | 90 | 20k  |

为提高产品性能和可靠性，所示尺寸和数值可在不事先通知的情况下更改。

Transfer Oil S.p.A.对本规格表中出现的错误不承担任何责任。

文本日期: 18/04/2025

[www.transferoil.com](http://www.transferoil.com)